

FICHA TECNICA

Producto : Selector amperimetrico
Marca : Salzer
Modelo : S16-61331
Amps : 16A
Caract. : 0-R-S-T 2 trafos
Certificac. :    




| AC Rating Code | Unit | S16/TP16/ RT16 |
|--|--------|---------------------|
| Rated Operational Voltage(Ue) | V | 690 |
| Rated frequency | Hz | 50/60 |
| Rated impulse withstand Voltage(Uimp) | Kv | 6 |
| Rated Operational Current(Ie) AC21/AC1 | A | 16 |
| Rated Uninterrupted Current (Ith) | A | 20 |
| Rated Operational Power | | |
| AC23A *3 Ph , 415 V" | KW | 7.5 |
| | A | 13 |
| AC3 | KW | 5.5 |
| "3 Ph , 415 V" | A | 10 |
| Short Circuit Capacity | | |
| Rated Fuse Short Circuit Current | KA | 5 |
| Fuse Size (Type gG/gM) | A | 16 |
| Terminal Cross Section | | |
| Single / Multiple | min | mm ² 1.5 |
| | max | mm ² 4 |
| Fine strand | min | mm ² 1 |
| | max | mm ² 2.5 |
| Terminal Cross Section | Metric | M3.5 |
| Terminal Tightening Torque | Nm | 0.8 |

CSA/UL Ratings


| AC Rating Code | Unit | S16 TP16 RT16 |
|------------------------|------|---------------------|
| Ampere Rating | A | 15 |
| Operational Voltage | V | 600 |
| HP Rating 1 Phase 120V | HP | 0.33 |
| 240V | HP | 1 |
| 3 Phase 120V | HP | 1.5 |
| 240V | HP | 3 |
| 480V | HP | 3 |
| 600V | HP | 5 |

61331



90 Degree

Connecting Diagram



SELECTOR AMPERIMETRICO 1 POLO 2 TRANSFORMADORES

